

S E R V I C E B U L L E T I N N O . 1 9 0**New software for turn-knob control**

To increase and strengthen our competitive power, we have introduced a new software version (3.30) for the turn-knob control, which makes it possible for a turn-knob oven to hold 50 programs with 10 process steps each.

When you update a control to a 3.30 version from a previous 3.xx version with a memory key, follow these instructions:

1. Go to b19 and run a backup for the IO board.
2. Update the control to version 3.30.
3. Go to b20 and read in the backup by pressing the alarm key.
4. In b20, press the fan key **only once** to activate all saved recipes.
5. Check that all programs are correct. If they are, run a new backup for the IO board using b19. If they are not, return to step 3 and start again.

When you change a CPU (part No. 30900054) to hold 50 programs instead of 10, this version will have No. 3.30. Follow these instructions to make the change:

1. Go to b20 and read in the backup by pressing the alarm key.
2. In b20, press the fan key **only once** to activate all saved recipes (*if you press the key more than once, it will not be possible to reactivate the recipes*).
3. Run a new backup for the IO board using b19.

(For customers with special program packages):

When you order a CPU (part No. 30900054), it will be delivered without a preprogrammed program package. If you would like a specific program package, you should mention this in your order.

The new software is introduced as from serial No. 11 12 5xxxx.

Best regards,

Michael Bech Jensen
Technical Support Manager – Customer Centre

Direct: +45 87 11 47 46
Mobile: +45 40 57 75 19
E-mail: mbj@houno.com

Skype Name: mbj.houno



Alsvej 1 ♦ 8940 Randers SV ♦ Denmark
Tel.: +45 87 11 47 11
www.houno.com